



AUBURN

UNIVERSITY

RFID LAB

TAGGED CATEGORY PERFORMANCE SPECIFICATION

W3

VERSION 1.1

Copyright © 2009-2019 ARC

Contact information:

ARC - RFID Lab
Auburn University
Auburn, AL 36849
rfidlab@auburn.edu



TABLE OF CONTENTS

1 Test Overview	3
2 Read Sensitivity	4
2.1 Standard Test - Single Inlay on Cardstock	5
2.2 Standard Test - Multi Inlay Proximity Test with 2.54 cm Spacing	6
2.3 Custom Test - Single Inlay between Two Denim Articles	7
2.4 Custom Test - Single Inlay between Ten Denim Articles	8
2.5 Standard Test - Single Inlay on Rubber2.....	9
3. Read Backscatter	10
3.1 Standard Test - Single Inlay on Cardstock	11
3.2 Custom Test - Single Inlay between Two Denim Articles	12



1 TEST OVERVIEW

Equipment	ARC Benchmarking Equipment Document
Test process	ARC Benchmarking Methodology Document
Distance between antennas and inlay	Antenna 1: 1.5 meter Antenna 2: 1.5 meter Antenna 3: 1.5 meter Antenna 4: 1.5 meter
Test configurations	Single Inlay on Cardstock Multi Inlay Proximity Test with 2.54 cm Spacing Single Inlay between Two Denim Articles Single Inlay between Ten Denim Articles Single Inlay on Rubber2 (Please refer ARC Testing Methodology)



2 READ SENSITIVITY

The inlay should meet the following read sensitivity (dBm) requirements in the following test configurations through the frequency range. All of the inlay samples tested should meet the minimum requirements. It is noted that the sensitivity is calculated at the tag by calibrating the measured power at the transmitter with the loss/gain during transmission.



2.1 Standard Test - Single Inlay on Cardstock

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-14.5	-13	-13.5	-13.5
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
-11.5	-11.5	-11.5	-11.5
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
-5	-5	-5	-2
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
-5	-5	-5	-2
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
-11.5	-11.5	-11.5	-11.5
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-14.5	-13	-13.5	-13.5
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
-11.5	-11.5	-11.5	-11.5
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
-5	-5	-5	-2
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
-5	-5	-5	-2
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
-11.5	-11.5	-11.5	-11.5



2.2 Standard Test - Multi Inlay Proximity Test with 2.54 cm Spacing

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-4	-4	-6	-1
Position 180: Ant 1	Position 180: Ant 2	Position180: Ant 3	Position 180: Ant 4
-4	-4	-6	-1



2.3 Custom Test - Single Inlay between Two Denim Articles

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-13	-11.5	-12	-11.5
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
-9.5	-9	-9	-9
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
-3.5	-3	-3	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
-3.5	-3	-3	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
-9.5	-9	-9	-9
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-13	-11.5	-12	-11.5
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
-9.5	-9	-9	-9
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
-3.5	-3	-3	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
-3.5	-3	-3	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
-9.5	-9	-9	-9



2.4 Custom Test - Single Inlay between Ten Denim Articles

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-11	-9	-9.5	-9.5
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
-8	-7	-6.5	-7
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
NA	NA	NA	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
NA	NA	NA	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
-8	-7	-6.5	-7
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-11	-9	-9.5	-9.5
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
-8	-7	-6.5	-7
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
NA	NA	NA	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
NA	NA	NA	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
-8	-7	-6.5	-7



2.5 Standard Test - Single Inlay on Rubber2

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-8	-7	-6	-6
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
NA	NA	NA	NA
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
NA	NA	NA	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
NA	NA	NA	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
NA	NA	NA	NA
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-8	-7	-6	-6
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
NA	NA	NA	NA
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
NA	NA	NA	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
NA	NA	NA	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
NA	NA	NA	NA



3. READ BACKSCATTER

The inlay should meet the following read backscatter (dBm) requirements in the following test configurations through the entire frequency range. The backscatter value in this section is the minimum backscatter that should be observed at the corresponding minimum read sensitivity value in section 2. All of the tagged item samples tested should meet the minimum requirements. It is noted that the backscatter is calculated at the tag by calibrating the measured power at the receiver with the loss/gain during transmission



3.1 Standard Test - Single Inlay on Cardstock

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-24	-25	-25	-24
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
NA	NA	NA	NA
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
NA	NA	NA	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
NA	NA	NA	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
NA	NA	NA	NA
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-24	-25	-25	-24
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
NA	NA	NA	NA
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
NA	NA	NA	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
NA	NA	NA	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
NA	NA	NA	NA



3.2 Custom Test - Single Inlay between Two Denim Articles

Frequency 902 MHz to 928 MHz in steps of 1 MHz

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-25	-28	-28	-26.5
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
NA	NA	NA	NA
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
NA	NA	NA	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
NA	NA	NA	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
NA	NA	NA	NA
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-25	-28	-28	-26.5
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
NA	NA	NA	NA
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
NA	NA	NA	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
NA	NA	NA	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
NA	NA	NA	NA