



AUBURN

UNIVERSITY

RFID LAB

TAGGED CATEGORY PERFORMANCE SPECIFICATION

CATEGORY I

VERSION 2.1

Copyright © 2009-2024 ARC

Contact information:

RFID Lab
Auburn University
Auburn, AL 36849
arc@rfidlab.org



TABLE OF CONTENTS

1 Test Overview	3
2 Read Sensitivity	4
2.1 Standard Test - Single Inlay on Cardstock	5
2.2 Standard Test - Multi Inlay Proximity Test with 1.27 cm Spacing	6
2.3 Standard Test - Single Inlay on Plastic3	7
3. Read Backscatter	8
3.1 Standard Test - Single Inlay on Cardstock	9



1 TEST OVERVIEW

Equipment	ARC Benchmarking Equipment Document
Test process	ARC Benchmarking Methodology
Frequency	865 MHz to 868 MHz in steps of 1 MHz
Distance between antennas and inlay	Antenna 1: 1 meter Antenna 2: 1meter Antenna 3: 1meter Antenna 4: 1 meter
Standard test configurations	Single Inlay on Cardstock Multi Inlay Proximity Test with 1.27cm Spacing Single Inlay on Plastic3



2 READ SENSITIVITY

The inlay should meet the following read sensitivity requirements in the following test configurations through the frequency range. All the inlay samples tested should meet the minimum requirements. It is noted that the sensitivity is calculated at the tag by calibrating the measured power at the transmitter with the loss during transmission.



2.1 Standard Test - Single Inlay on Cardstock

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-11	-11	-11	-11
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
-9	-9	-8.5	-8
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
-2.5	-2.5	-1	3.5
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
-2.5	-2.5	-1	3.5
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
-9	-9	-8.5	-8
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-11	-11	-11	-11
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
-9	-9	-8.5	-8
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
-2.5	-2.5	-1	3.5
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
-2.5	-2.5	-1	3.5
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
-9	-9	-8.5	-8



2.2 Standard Test - Multi Inlay Proximity Test with 1.27 cm Spacing

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
1	-4	-6	-1
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
5	-2	-4	2
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
5	-2	-4	2
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
1	-4	-6	-1
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
5	-2	-4	2
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
5	-2	-4	2



2.3 Standard Test - Single Inlay on Plastic3

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-13	-12.5	-12	-12
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
-11	-11	-10.5	-10
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
-4	-4	-2.5	2.5
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
-4	-4	-2.5	2.5
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
-11	-11	-10.5	-10
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-13	-12.5	-12	-12
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
-11	-11	-10.5	-10
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
-4	-4	-2.5	2.5
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
-4	-4	-2.5	2.5
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
-11	-11	-10.5	-10



3. READ BACKSCATTER

The inlay should meet the following read backscatter (dBm) requirements in the following test configurations through the entire frequency range. The backscatter value in the table below is the minimum backscatter that should be observed at the corresponding minimum read sensitivity value in section 3. All the tagged item samples tested should meet the minimum requirements. It is noted that the backscatter is calculated at the tag by calibrating the measured power at the receiver with the loss/gain during transmission



3.1 Standard Test - Single Inlay on Cardstock

Position 0 Ant 1	Position 0: Ant 2	Position 0: Ant 3	Position 0: Ant 4
-26	NA	NA	NA
Position 30: Ant 1	Position 30: Ant 2	Position 30: Ant 3	Position 30: Ant 4
NA	NA	NA	NA
Position 60: Ant 1	Position 60: Ant 2	Position 60: Ant 3	Position 60: Ant 4
NA	NA	NA	NA
Position 120: Ant 1	Position 120: Ant 2	Position 120: Ant 3	Position 120: Ant 4
NA	NA	NA	NA
Position 150: Ant 1	Position 150: Ant 2	Position 150: Ant 3	Position 150: Ant 4
NA	NA	NA	NA
Position 180: Ant 1	Position 180: Ant 2	Position 180: Ant 3	Position 180: Ant 4
-26	NA	NA	NA
Position 210: Ant 1	Position 210: Ant 2	Position 210: Ant 3	Position 210: Ant 4
NA	NA	NA	NA
Position 240: Ant 1	Position 240: Ant 2	Position 240: Ant 3	Position 240: Ant 4
NA	NA	NA	NA
Position 300: Ant 1	Position 300: Ant 2	Position 300: Ant 3	Position 300: Ant 4
NA	NA	NA	NA
Position 330 Ant 1	Position 330: Ant 2	Position 330: Ant 3	Position 330: Ant 4
NA	NA	NA	NA